



Tech Info Library

Apple IIc: Cable structure to Nec 2015 Spinwriter

Revised: 11/7/85
Security: Everyone

Apple IIc: Cable structure to Nec 2015 Spinwriter

=====

APPLE IIC	NEC 2015 SPINWRITER
-----------	---------------------

2-----	3
3-----	7
4-----	2
5-----	19
	4,5,6,8: Jumpered

NEC Dip switch settings:

Switch series 1: all off except #8
Switch series 2: all off
Switch series 3: all off except #4,6,7,8.

Clinton Computer, MD

Tech Info Library Article Number:1447